

Installation and Operation Instructions

ED3766 Directional LED

IMPORTANT! Read all instructions before installing and using. Installer: This manual must be delivered to the end user.



WARNING

Failure to install or use this product according to manufacturer's recommendations may result in property damage, serious injury, and/or death to those you are seeking to protect!



Do not install and/or operate this safety product unless you have read and understand the safety information contained

- Proper installation combined with operator training in the use, care, and maintenance of emergency warning devices are essential to ensure the safety of you and those you are seeking to protect.
- 2. Exercise caution when working with live electrical connections.
- This product must be properly grounded. Inadequate grounding and/or shorting of electrical connections can cause high current arcing, which can cause personal injury and/or severe vehicle damage, including fire.
- 4. Proper placement and installation are vital to the performance of this warning device. Install this product so that output performance of the system is maximized and the controls are placed within convenient reach of the operator so that s/he can operate the system without losing eye contact with the roadway.
- 5. Do not install this product or route any wires in the deployment area of an air bag. Equipment mounted or located in an air bag deployment area may reduce the effectiveness of the air bag or become a projectile that could cause serious personal injury or death. Refer to the vehicle owner's manual for the air bag deployment area. It is the responsibility of the user/operator to determine a suitable mounting location ensuring the safety of all passengers inside the vehicle particularly avoiding areas of potential head impact.
- It is the responsibility of the vehicle operator to ensure during use that all features of this product work correctly. In use, the vehicle operator should ensure the projection of the warning signal is not blocked by vehicle components (i.e., open trunks or compartment doors), people, vehicles or other obstructions.
- 7. The use of this or any other warning device does not ensure all drivers can or will observe or react to a warning signal. Never take the right-of-way for granted. It is your responsibility to be sure you can proceed safely before entering an intersection, driving against traffic, responding at a high rate of speed, or walking on or around traffic lanes.
- This equipment is intended for use by authorized personnel only. The user is responsible for understanding and obeying all laws regarding warning signal devices. Therefore, the user should check all applicable city, state, and federal laws and regulations. The manufacturer assumes no liability for any loss resulting from the use of this warning device.


Important! This unit is a safety device and it must be connected to its own separate, fused power point to assure its continued operation should any other electrical accessory fail.

Caution: When drilling into any vehicle surface, make sure the area is free from any electrical wires, fuel lines, vehicle upholstery, etc. that could be damaged

SPECIFICATIONS:

Input Voltage	12-24VDC
Work Current	0.9A Max @ DC12V 0.5A Max @ DC24V
Physical H x W x L	1.07 in x 1.48 in x 6.38 in 2.76 cm x 3.75 cm x 16.2 cm
Ship Weight	0.463 lb (0.21 Kg)

Mounting:



Wire:

RED: Positive, Colors 1 & 3 (need to add 5A fuse) WHITE: Positive, Colors 2 & 4 (need to add 5A fuse) BLACK: Negative BLUE: Pattern select to negative YELLOW: Synchronized Function (Up to 8 units can be Synchronized)

Phase Operation:

Phase 1 (Ph1) flashes simultaneously with Ph1 Phase 2 (Ph2) flashes simultaneously with Ph2 Ph1 alternates with Ph2 (Up to 8 units can be Synchronized)

Apply BLUE TO BLACK wire:

-Less than 1 sec. for next pattern -Between 1-3 sec for previous pattern -Between 3-5 sec. for factory default -More than 5 sec. for steady burn

Operation Environment:

Ambient Temperature: -30 to 50°C

TroubleshootingThe ED3766 series has been factory tested and approved. If the functions of the device fail, please check the following:

- 1. After connecting with the power supply, be sure that the power source end is joined correctly. Make sure there is not a short circuit.
- 2. Plug in the device; ensure the LED power switch is on.
- 3. If the blue wire touches the black wire over 5 seconds, it would switch to the steady burn pattern. It will light up again when the blue wire touches the black wire continuously for less than 1 second.

DUAL COLOR Flash Patt 3 art/COLOR DOBLE Tabla de de destello/BICOLORE Table offoto

	12	= 5	5	o «	7									۰				»							s								4								w	,							7	,							_	-				Pattern	
	36				35	34	33				32	31	30	29	28				27	26	25	24	23					22	21	70	18					17	16	15	1.4	:				12	11	10	9	e				7	6	5	4	دي				2	1-Default	LED Color 1 & Color 3 Red line	
36					35	34	8	23	*				30	29	28	70	2				25	24	23	22	21				200	3) 19	5 56	17	16					15 14	14	12	=					10	9	9	3 0					5	4	.	1-Default					LED Color 1 & Color LED Color 2 & Color 3 Red line 4 White line	IJ
69	68	67	66	65	63	62	61	60	58	57	56	55	54	53	52-Default	18	49	48	47	46	45	44	43	42	41	40	39	38	37	36	34	33	32	31	30	29	28	26	2.5	24	23	22	21	20	19	18	17	16	1 4	13	12	111	10	9	88	7	n un	. 4	3	2	Red & White line	EE	UAL COLOR
Steady burn-Color 2 & 4	Steadyburn-Color 1 & 3	1 Doube 1 Triple 1 Quad (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	Synchronius Color 3) Alternately (Color 2 Synchron	Modulation (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4) 2 Double 2 Quad (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	mately ((Color 1 Synchronous Color 3) Alternately	Quad 60 FPM Fh 1 (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	Quid 120FPM Ph Color 2 Synchronous Color 4 Oud 120FPM Ph Color 2 Synchronous Color 4	Quad 120FPM Ph2 Color 1 Alternately Color 4	Quad 60FPM Ph 1 Color 1 Alternately Color 4	Quad 120FPM Ph2 Color 1 Synchronous Color 3		mately Color 2) Alternately (Color 3 Alternately Color 4	Synchronous Color 3) Altem	Quad 38 FPM Ph 1 (Co.kr. 1 Synchronous Color 3) Alternately (Co.kr. 2 Synchronous Color 4)	Quad /SEPM IN Color 2 Synchronous Color 4	Quad 75FPM Ph2 Color I Alternately Color 4	Quad 75FPM Ph1 Coker 1 Alternately Coker 4	Quad 75FPM Ph2 Coker 1 Synchronous Color 3	Quad 75FPM Ph 1 Color 1 Synchronous Color 3	Triple 38FPM (Cokr 1 Alternately Color 2) Alternately (Color 3 Alternately Color 4)	Triple 38FPM Ph2 (Coker 1 Synchronous Color 3) Alternately (Coker 2 Synchronous Color 4)	Triple 38FPM Ph1 (Coker 1 Synchronous Color 3) Alternately (Coker 2 Synchronous Color 4)	Triple 75FPM Ph2 Color 2 Synchronous Color 4	Table 75FPM Ph1 Color 2 Synchronous Color 4	Triple 75FPM Ph2 Coker 1 Alternately Coker 4	Table 75 FPM Ph Coker 1 Alternately Coker 4	Triple 75 FPM Pt2 Color 1 Synchronous Color 3	Table 2SERM Ph Cohe I Sundroman Color 3	Double 60FPM (Color 1 Alternately Color 2) Alternately (Color 2 Synchrobous Color 4) Double 60FPM (Color 1 Alternately Color 2) Alternately (Color 3 Alternately Color 4)	Double 60FPM Ph1 (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	Double 120FPM Ph2 Color 2 Synchronous Color 4	Double 120FPM Ph1 Color 2 Synchronous Color 4	Double 120 FPM Ph2 Color 1 Alternately Color 4	Double 120FPM Ph1 Color 1 Alternately Color 4	Double 120 FPM Ph 2 Coker 1 Synchronous Color 3	Double 120 FPM 18 1 Color 1 Synchronous Color 3 Double 120 FPM 18 1 Color 1 Synchronous Color 3	Double 38FPM Ptz (Color L Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	Double 38FPM Ph1 (Color 1 Synchronous Coker 3) Alternately (Color 2 Synchronous Coker 4)	Double 75FPM Ph2 Color 2 Synchronous Color 4	Double 75FPM Ph1 Color 2 Synchronous Color 4	Double 75FPM Ph2 Color 1 Alternately Color 4	Double 75FPM Ph1 Color 1 Alternately Color 4	Double 75FPM Ph2 Color 1 Synchronous Color 3	Double 75FPM Ph1 Color 1 Synchronous Color 3	lor 1 Alternately Color 2) Alternately (Color 3 Alternately C	Single 187FPMFPM Ph2 (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	1) Alternatals (Color 2 Sanchuspers	Single 3 (3HPMHPM Ph I Color 2 Synchronous Color 4	Ph2 Color 1	Ph I Color 1 Alternately C	Single 375FPMFPM Ph2 Color 1 Synchronous Color 3	Synchronous Color 3	Single 38FPM (Color 1 Alternately Color 2) Alternately (Color 3 Alternately Color 4)	ately (Color 2 Synchronou	Single 38FPM Ph1 (Color 1 Synchronous Color 3) Alternately (Color 2 Synchronous Color 4)	Single 75FPM Ph1 Color 2 Synchronous Color 4	Color I	Single 75FPM Ph1 Color 1 Alternately Color 4	Single 75FPM Ph2 Color 1 Synchronous Color 3	Single 75FPM Ph1 Color 1 Synchronous Color 3	PATTERNS	DUAL COLOR Flash Pattern Chart/COLOR DOBLE Tabla de patrones de destello/BICOLORE Tableau des effets elignotants
		N/A				711				Б.				m				>				т				Þ					n				D			,	n			:	Þ				I				o				m				Þ			Mark	lestello/
по	no	no lo	3 8	B 100	yes	yes	yes	yes	yes	yes	yes	yes	yes	ves	ves	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	yes	ves	ves	yes	yes	yes	yes	yes	yes	yes	ves	ves	yes	yes	yes	yes	yes	yes	yes	yes	yes	ves	yes	yes	yes	yes	yes	yes	yes	yes	ves	yes	yes	yes	yes	ves	SYNC.	BICO
N/C	N/C	N/C	N/C	Z Z	N/C	N/C	N/C	Class	N/C	N/C	Class 1	Class 1	N/C	N/C	N/C	Class I	N/C	N/C	Class 1	Class 1	N/C	N/C	N/C	Class 1	Class 1	N/C	N/C	Class 1	Class	N/C	N/C	Class 1	Class 1	N/C	N/C	Class I	Class 1	N/C	N C	Class 1	Class 1	N/C	N/C	Class 1	Class 1	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	Class I	N/C	N/C	Class 1	Class 1		LORE
N/C	N/C	N/C	N/C	Z Z	N/C	N/C	N/C	Class I	N/C	N/C	Class I	Class 1	N/C	N/C	N/C	Class I	N/C	N/C	Class 1	Class 1	N/C	N/C	N/C	Class 1	Class 1	N/C	N/C	Class 1	Class	N/C	N/C	Class 1	Class 1	N/C	N/C	Class I	Class 1	N/C	N/C	Class 1	Class 1	N/C	N/C	Class 1	Class I	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	Class 1	N/C	N/C	Class 1	Class 1	IVS	Table
N/C	N/C	N/C	N/C	Z Z	N/C	N/C	N/C	Class I	N/C	N/C	Class 1	Class 1	N/C	N/C	N/C	Class I	N/C	N/C	Class 1	Class 1	N/C	N/C	N/C	Class 1	Class 1	N/C	N/C	Class I	Class	N/C	N/C	Class 1	Class 1	N/C	N/C	Class I	Class 1	N/C	X X	Class 1	Class 1	N/C	N/C	Class 1	Class I	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	Class I	N/C	N/C	Class 1	Class 1	SAE JS95	eau de
N/C	N/C	NC S	N S	Z Z	N/C	N/C	N/C	Class 2	NC	N/C	Class 2	Class 2	N/C	NC S	N/C	Class 2	NC	NC	Class 2	Class 2	N/C	N/C	N/C	Class 2	Class 2	N/C	N/C	Class 2	Class	N C	X C	Class I	Class 1	N/C	N/C	Class I	Class I	NIC O	N C	Class 1	Class 1	NC	NC	Class l	Class I	N/C	N/C	NIC O	N C	NC.	NC	N/C	N/C	N/C	NC	N/C	Class I	N/C	N/C	Class 1	Class 1		s effet
N/C	N/C	N/C	N/O	Z Z	N/C	N/C	N/C	Z Z	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N N	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	Class B	N/C	N/C	Class B	Class B		s clign						
N/C	N/C	N/C	N S	Z Z	N/C	N/C	N.C	Z Z	NC NC	N/C	N/C	N/C	N/C	NC.	N S	N N	NC NC	N/C	NC	N/C	N/C	N/C	N/C	N/C	N/C	N/C	NO.	NC S	200	N N	NC NC	N/C	N/C	N/C	N/C	NC C	N is	NIC NIC	N C	N/C	NC	N/C	N/C	N/C	N/C	N/C	NC C	NIC NIC	NC NC	NC	NC	N/C	N/C	N/C	NC.	+	Class B	_	N/C	$^{+}$	Class B	CA TI3	otants
N/C	N/C	N/C	N S	Z Z	N/C	N/C	N/C	2 2	N.C	N/C	N/C	N/C	N/C	N.C	N/C	N N	N.C	N/C	NC	NC	NC	NC	NC	N.C	N/C	N/C	NC.	N/C	N S	N N	N.C	N/C	N/C	N/C	N/C	N/C	N.C	N N	N N	N/C	NC	N/C	N/C	NC	N/C	N/C	N/C	N N	N.C	N.C	N.C	N/C	N/C	N/C	N.C	+	Class B	N/C	N/C	$^{+}$	Class B	1	
N/C	N/C	N/C	N/O	Z Z	N/C	N/C	N/C	ZZ	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N N	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N G	N/C	N/C	Class 1	Class 1	N/C	N/C	Class 1	Ches 1	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C		П	N/C		
N/C	N/C	N/C	N S	Z Z	N/C	N/C	N/C	Z Z	NC.	N/C	N/C	N/C	N/C	NC.	N S	N N	NC	NC	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	NC.	NC S	N/C	NIC NC	NC.	Class 1	Class 1	N/C	N/C	Class 1	Class	NIC	N C	N/C	NC	N/C	N/C	N/C	N/C	N/C	N.C	NIC	N C	NC	NC	N/C	N/C	N/C	NC	NC S	N/C	N/C	N/C	N/C	N/C	ECE R65	
N/C	N/C	N/C	Z S	Z Z	N/C	N/C	N/C	ZZ	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	NIC	N/C	N/C	Class 1	Class 1	N/C	N/C	Class I	Class 1	NIC	N C	N/C	N/C	N/C	Z Z	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C	N/C								

Manufacturer Limited Warranty and Limitation of Liability:

Manufacturer warrants that on the date of purchase, this product will conform to Manufacturer's specifications for this product (which are available from the Manufacturer upon request). This Limited Warranty extends for sixty (60) months from the date of purchase.

DAMAGE TO PARTS OR PRODUCTS RESULTING FROM TAMPERING, ACCIDENT, ABUSE, MISUSE, NEGLIGENCE, UNAPPROVED MODIFICATIONS, FIRE OR OTHER HAZARD; IMPROPER INSTALLATION OR OPERATION; OR NOT BEING MAINTAINED IN ACCORDANCE WITH THE MAINTENANCE PROCEDURES SET FORTH IN MANUFACTURERS INSTALLATION AND OPERATING INSTRUCTIONS VOIDS THIS LIMITED WARRANTY.

Exclusion of Other Warranties:

MANUFACTURER MAKES NO OTHER WARRANTIES, EXPRESSED OR IMPLIED. THE IMPLIED WARRANTIES FOR MERCHANTABILITY, QUALITY OR FITNESS FOR A PARTICULAR PURPOSE, OR ARISING FROM A COURSE OF DEALING, USAGE OR TRADE PRACTICE ARE HEREBY EXCLUDED AND SHALL NOT APPLY TO THE PRODUCT AND ARE HEREBY DISCLAIMED, EXCEPT TO THE EXTENT PROHIBITED BY APPLICABLE LAW. ORAL STATEMENTS OR REPRESENTATIONS ABOUT THE PRODUCT DO NOT CONSTITUTE WARRANTIES.

Remedies and Limitation of Liability:

MANUFACTURER'S SOLE LIABILITY AND BUYER'S EXCLUSIVE REMEDY IN CONTRACT, TORT (INCLUDING NEGLIGENCE), OR UNDER ANY OTHER THEORY AGAINST MANUFACTURER REGARDING THE PRODUCT AND ITS USE SHALL BE, AT MANUFACTURER'S DISCRETION, THE REPLACEMENT OR REPAIR OF THE PRODUCT, OR THE REFUND OF THE PURCHASE PRICE PAID BY BUYER FOR NON-CONFORMING PRODUCT. IN NO EVENT SHALL MANUFACTURER'S LIABILITY ARISING OUT OF THIS LIMITED WARRANTY OR ANY OTHER CLAIM RELATED TO THE MANUFACTURER'S PRODUCTS EXCEED THE AMOUNT PAID FOR THE PRODUCT BY BUYER AT THE TIME OF THE ORIGINAL PURCHASE. IN NO EVENT SHALL MANUFACTURER BE LIABLE FOR LOST PROFITS, THE COST OF SUBSTITUTE EQUIPMENT OR LABOR, PROPERTY DAMAGE, OR OTHER SPECIAL, CONSEQUENTIAL, OR INCIDENTAL DAMAGES BASED UPON ANY CLAIM FOR BREACH OF CONTRACT, IMPROPER INSTALLATION, NEGLIGENCE, OR OTHER CLAIM, EVEN IF MANUFACTURER OR A MANUFACTURER SEPECIAL TO THE PRODUCT OR THE POSSIBILITY OF SUCH DAMAGES. MANUFACTURER SHALL HAVE NO FURTHER OBLIGATION OR LIABILITY WITH RESPECT TO THE PRODUCT OR ITS SALE, OPERATION AND USE, AND MANUFACTURER NEITHER ASSUMES NOR AUTHORIZES THE ASSUMEND OR ANY OTHER OBLIGATION OR LIABILITY OR PRODUCT.

This Limited Warranty defines specific legal rights. You may have other legal rights which vary from jurisdiction to jurisdiction. Some jurisdictions do not allow the exclusion or limitation of incidental or consequential damages.