



Description

When wiring independent lights:

- RED is 12v (+), wire to *your* switch to turn lights on
- Black is ground (-)
- Yellow is trigger wire, touch to 12v + to change patterns

When wiring 2 or more lights to synchronize:

- All Red wires together 12v (+) to *your* switch to turn lights on
- All Black wires together to ground (-)
- All Green wires must be tied together
- All Yellow wires must be tied together and then touch to 12v + to change patterns

NOTE for synchronizing * after attaching all wires, (turn on power) touch and HOLD yellow wire to 12v + for 2-3 seconds and ALL lights will go out for one second and then come back on. They are now synchronized and every time you touch yellow wire to 12v + it will change the pattern on all lights.

When wiring 2 or more lights to “wig-wag” asynchronization :

- Follow instructions for synchronizing and then attach ONE green wire to power (hot wire) and lights will wig-wag back and forth.